

Splice Tray Bracket

For PCH-04U

CORNING

Splice Tray Bracket

Corning splice tray bracket for PCH-04U accepts up to 12 0.2-in Type 2S or seven 0.4-in Type 4S standard length splice trays. The bracket also accepts up to 12 0.2-in Type 2R or seven 0.4-in Type 4R splice trays. The splice tray bracket works with cable entry from the left-hand side only.



Ordering Information

Part Number	PC4-SPLC-12SR
Product Description	Splice Tray Bracket for PCH-04U; accepts up to (12) 0.2 in Category 2S or (7) 0.4 in Category 4S standard length splice trays; or accepts up to (12) 0.2 in Category 2R or (7) 0.4 in Category 4R splice trays; works with cable entry from the left-hand side only
EAN Code	4056418201955

Shipping Information

Package Contents	Swing-out Splice Tray Bracket; installation guide; label, splicing assignment; 2 screws, #6-32 x 0.5-in; 3 wing nuts, #6-32 and 4 tie wraps, 1/8 x 4, white
Units per Delivery	1/1

CORNING

Splice Tray Bracket

For PCH-04U

The CORNING logo is displayed in white, uppercase letters within a solid blue square.

Notes



Corning Optical Communications LLC • PO Box 489 • Hickory, NC 28603-0489 USA

800-743-2675 • FAX: 828-325-5060 • International: +1-828-901-5000 • www.corning.com/opcomm

A complete listing of the trademarks of Corning Optical Communications is available at www.corning.com/opcomm/trademarks.

All other trademarks are the properties of their respective owners. Corning Optical Communications is ISO 9001 certified.

© 2016 Corning Optical Communications. All rights reserved.